

Re-banding Requests Received Between the Completion of the Allocations for ET3 and the Commencement of the ET3 Price Control Period.

- Re-banding requests received after the allocations for the ET3 Price Control Period have been completed, but prior to 1 April 2026, should be treated as two separate allocations:
 - one allocation for the current Price Control Period (“ET2”); and
 - one allocation for the next Price Control Period (“ET3”).
- For the ET2 Price Control Period, the re-banding request must be assessed against:
 - a) The thresholds for the ET2 Price Control Period; and
 - b) The MIC at the time of the last ET2 (or current) allocation.Upon successful application this would take effect now
- For the ET3 Price Control Period, the re-banding request must be assessed against:
 - a) the thresholds for the ET3 Price Control Period; and
 - b) The MIC at the time of the ET3 allocation period;Upon successful application this would take effect from 01/04/2026.

A typical LV MIC site example below.

- The site had a MIC of 120kVA from 2015 to 2023.
 - The site had an average MIC of 120kVA in the ET2 allocations, and their MIC was 120kVA when they were allocated.
 - The site was allocated to LV band 2 and must reduce the MIC to 59kVA (or lower) to be eligible for an ET2 reallocation to LV band 1.
 - In January 2023 the site increased their MIC to 180kVA, and remained in LV band 2.
 - The average MIC was 180kVA in the initial ET3 allocations, and the MIC was 180kVA when the ET3 allocation took place.
 - They were allocated to LV band 3 from April 2026 and must reduce the MIC to 89kVA (or lower) to be eligible for an ET3 reallocation.
- If the customer reduces the MIC to 59kVA they would be eligible for a reallocation to band 1 for the current allocation (ET2) AND for the ET3 allocation.
- If the customer reduces the MIC to 89kVA they would only be eligible for an ET3 reallocation and would not be eligible for an ET2 reallocation because:
- For ET2:
 - They have not met the minimum 50% threshold against the MIC at the time of the ET2 allocation (120kVA); and
 - In this instance the reduction (even if it met the 50%) is still within ET2 band 2 thresholds.
 - For ET3:
 - They have met the minimum 50% threshold against the MIC at the time of the ET3 allocation (180kVA); and
 - In this instance the reduction is within the ET3 band 1 thresholds.

- When the migration to ET3 bands takes place in April 2026, this customer would be migrated to band 1 rather than band 3 as they were in the initial ET3 allocations.